



Description

Optimized for the real-world audiophile who demands flexibility and sound quality at an affordable price, the RC-1070 preamplifier delivers an extraordinary level of satisfaction. Featuring traditional Rotel engineering prowess, this unit features a power supply based on a custom-made toroidal transformer. The RC-1070 provides six line-level inputs in addition to a carefully engineered phono input for moving magnet and high output moving coil cartridges. A convenient contour control allows easy and repeatable timbre adjustments. With two sets of main outputs, a 12 volt “trigger” jack, and a Rotel-system remote control for both the preamplifier and a companion Rotel CD, tuner, or DVD player, the RC-1070 brings the flexibility and sound quality of Rotel separates within easy reach.

Specifications

THD (20-20kHz):	0.006%	Tone Control:	
IM Distortion:	0.006% @ 1v out	Bass	+3, -4dB at 100Hz
Input Sens. / Impedance:		Treble	=dB at 10kHz
Phono (MC)	250 mV / 100 ohms	S/N Ratio (IHF A)	
Phono (MM)	1.2 mV / 68 K ohms	Phono (MM)	70 dB
Line level inputs	150 mV / 24 K ohms	Line Level Input	95 dB
Phono Overload (MC/MM):	16 mV / 160 mV	Power Consumption:	10 watts
Output Sens. / Impedance:	1V / 100 ohms	Dimensions (W x H x D):	430 x 92 x 334 mm
Frequency Response:			17 1/8 x 3 5/8 x 13 1/8 in
Phono input	20-20k Hz (±0.5dB)	Front Panel Height:	80 mm, 3.1 in
Line Level Input	4-100k Hz (+0, -3dB)	Weight (net):	5.4 kg / 11.9 lbs

www.rotel.com

The Rotel Co. Ltd.
10-10 Shinsen-Cho
Shibuya-Ku,
Tokyo 150, Japan

Rotel of America
54 Concord St.
N. Reading, MA 01864
USA
T +1 978 664 3820
F +1 978 664 4109

Rotel Europe
Dale Road
Worthing
West Sussex BN11 2BH, UK
T +44 (0) 1903 221 763
F +44 (0) 1903 221 525